



Horizon LED Linear Light 8050

Hanging Installation


Step 1: Accessories

| a. | 8050 lamp | 1pcs | b. square-headed screw | 4pcs | c. | safety rope | 2pcs | d. fixing head 3 4pcs |
|----|----------------|------|---------------------------|------|----|---------------|------|------------------------|
| e. | sewing machine | 2pcs | f. suspended rope | 2pcs | g. | fixing head 1 | 2pcs | h. 4*30PA screw 2pcs |
| i. | fixing head 2 | 2pcs | j. rubber plug | 2pcs | k. | fixing head 3 | 4pcs | I. doubling clamp 4pcs |
| m | ccrow | 2ncs | | | | | | |






Step 2: Drill holes in the ceiling, push the rubber plug into the ceiling, fix the fixing head 2 in the ceiling with 4*30PA screws.




Step 3: a. Thread the square-headed screw through fixing hole of safety rope, clamp and 8-figure buckle.
Fix firmly
b. Thread the square-headed screw through fixing hole of safety rope, clamp, and fix.



Step 4: Thread the power wire through 8-figure buckle fixed on the left, then install the whole set of fixing clips on the lamp.






Surface mounted

Step 1: Accessories

| a. | 8050 lamp | 1pcs | b. | 4*25PM screw | 2pcs | C. | clip | 2pcs | d. | rubber plug | 2pcs | 1 |
|----|-----------|------|----|--------------|------|----|------|------|----|-------------|------|---|
| | | 1 | | | | | - 1- | 1 | | 1 0 | 1 | П |





Step 2: Drill holes in the ceiling, and push rubber plug into the hole



Step 3: Thread 4*25PA screw through fixing hole of safety rope and clip, Fix 4*25PA screws and rubber plugs tightly.



Step 4: Connect input wire of lamp and install the lamp on the clip.